


- ◎ CPU control, Low frequency
- ◎ Pure sine wave output
- ◎ 10ms transfer time for AC to DC
- ◎ Input voltage range 80V~140V/160V~265V
- ◎ Input frequency range 45~55Hz/55~65Hz
- ◎ Easy to install, easy to use
- ◎ Intelligent automatic charging
- ◎ Overload, short circuit protection
- ◎ Over temperature protection
- ◎ Over voltage, low voltage protection
- ◎ Low battery protection
- ◎ Compatible with generators
- ◎ Using line interactive circuit technology
- ◎ Automatically AC bypass
- ◎ **Software & SNMP card optional with adding cost**



Technical Specifications

Model No.	PRNZ - 500VA
Output power	400W
Peak power	1200W (3s)
DC Input Voltage	12V/24V/48V
DC range	10-16V/20-32V/40-64V
Battery over voltage	16V/32V/64V
Charge current	15A - 30A
Output waveform	Pure sine wave
AC bypass	80-140V / 160-265V
Input frequency	55-65Hz / 45-55Hz
Overload capability	100%-125% warning; 125%-150% shut down after 30s; above 150% shut down immediately
AC over voltage	Above 140V or 265V, automatically change to inverter mode
AC lack voltage	Lower than 80V or 160V, automatically change to inverter mode
Changeover switch	8A
Transfer time	AC to DC 10ms, DC to AC 0ms
Utility efficiency	> 95%
Output power factor	0.8
Nominal output voltage	110V (120V) or 220V (230V)
Output voltage range	±10%
Output frequency	60Hz / 50Hz ±1%
Inverter efficiency	> 80%
Short circuit protection	less than 3s automatically shut down
Working temperature	-10°C ~ 40°C
Storage temperature	-20°C ~ 50°C
Working humidity	0% ~ 95% no condensation
Noise level	< 40dB (within 1meter)
LCD display	Optional (LCD menu with optional battery type, charge current, voltage, etc.)
Product dimension (mm)	425 x 143 x 215 mm
Packing size (cm)	50.5 x 26.5 x 30 cm
Gross weight (kg)	10kg
Net weight (kg)	8.2kg
Backup time	Inverter backup time (h) = battery capacity (Ah) / discharge current (A)
Battery mode	External Battery